


SMALL SIGNAL SCHOTTKY DIODE

DESCRIPTION

Metal to silicon junction diode featuring high breakdown, low turn-on voltage and ultrafast switching. Primarly intended for high level UHF/VHF detection and pulse application with broad dynamic range. Matched batches are available on request.



ABSOLUTE RATINGS (limiting values)

Symbol	Parameter	Value	Unit	
V_{RRM}	Repetitive Peak Reverse Voltage		70	V
I _F	Forward Continuous Current*	T _a = 25 °C	15	mA
P _{tot}	Power Dissipation*	T _a = 25°C	430	mW
T _{stg} T _j	Storage and Junction Temperature Range		- 65 to 200 - 65 to 200	°C
TL	Maximum Lead Temperature for Soldering during 10s at 4mm from Case		230	°C

THERMAL RESISTANCE

Symbol	Test Conditions	Value	Unit
R _{th(j-a)}	Junction-ambient*	400	°C/W

ELECTRICAL CHARACTERISTICS

STATIC CHARACTERISTICS

Symbol		Test Conditions	Min.	Тур.	Max.	Unit
V_{BR}	T _{amb} = 25°C	$I_R = 10\mu A$	70			٧
V _F * *	T _{amb} = 25°C	$I_F = 1 \text{mA}$			0.41	V
	T _{amb} = 25°C	$I_F = 15mA$			1	
I _R * *	T _{amb} = 25°C	V _R = 50V			0.2	μΑ

DYNAMIC CHARACTERISTICS

Symbol	Test Conditions			Min.	Тур.	Max.	Unit
С	T _{amb} = 25°C	$V_R = 0V$	f = 1MHz			2	рF
τ	T _{amb} = 25°C	$I_F = 5mA$	Krakauer Method			100	ps

* On infinite heatsink with 4mm lead length
** Pulse test: $t_p \le 300 \mu s \ \delta < 2\%$.
Matched batches available on request. Test conditions (forward voltage and/or capacitance) according to customer specification.

August 1999 Ed: 1A 1/3

Figure 1. Forward current versus forward voltage at low level (typical values).




Figure 2. Capacitance C versus reverse applied voltage $V_{\rm R}$ (typical values).




Figure 3. Reverse current versus ambient temperature.






Figure 4. Reverse current versus continuous reverse voltage (typical values).



2/3

PACKAGE MECHANICAL DATA

DO 35 Glass



Cooling method: by convection and conduction Marking: clear, ring at cathode end. Weight: 0.15g

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied.

STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval

STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a registered trademark of STMicroelectronics

© 1999 STMicroelectronics - Printed in Italy - All rights reserved.

STMicroelectronics GROUP OF COMPANIES

Australia - Brazil - China - Finland - France - Germany - Hong Kong - India - Italy - Japan - Malaysia Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - U.S.A.

http://www.st.com